

Page Mode Programming Conversion Chart

To access a CV using Page Mode, find the CV in the columns on the right. Enter the Page Address into Register 6. Then select the Register 1,2,3 or 4, 1,2,3 or 4, that the CV is listed under.

EX:

To access CV 55, load 14d* into Register 6, and use Register 3 to enter the data.

* This is a decimal number not hexadecimal.

Accessory Decoder Addresses				
Decimal				
Page Address	Data Register (RRR)			
Reg 6	Reg 1	Reg 2	Reg 3	Reg 4
Corresponding CV				
	ADR	Start V	Accel	Decel
1	1	2	3	4
2	5	6	7	8
3	9	10	11	12
4	13	14	15	16
5	17	18	19	20
6	21	22	23	24
7	25	26	27	28
8	29	30	31	32
9	33	34	35	36
10	37	38	39	40
11	41	42	43	44
12	45	46	47	48
13	49	50	51	52
14	53	54	55	56
15	57	58	59	60
16	61	62	63	64
17	65	66	67	68
18	69	70	71	72
19	73	74	75	76
20	77	78	79	80
21	81	82	83	84
22	85	86	87	88
23	89	90	91	92
24	93	94	95	96
25	97	98	99	100
26	101	102	103	104
27	105	106	107	108
28	109	110	111	112
29	113	114	115	116
30	117	118	119	120
31	121	122	123	124
32	125	126	127	128
33	129	130	131	132
34	133	134	135	136
35	137	138	139	140

	Accessory Decoder Addresses			
Decimal				
Page Address	Data Register (RRR)			
Reg 6	Reg 1	Reg 2	Reg 3	Reg 4
	Corresponding CV			
36	141	142	143	144
37	145	146	147	148
38	149	150	151	152
39	153	154	155	156
40	157	158	159	160
41	161	162	163	164
42	165	166	167	168
43	169	170	171	172
44	173	174	175	176
45	177	178	179	180
46	181	182	183	184
47	185	186	187	188
48	189	190	191	192
49	193	194	195	196
50	197	198	199	200
51	201	202	203	204
52	205	206	207	208
53	209	210	211	212
54	213	214	215	216
55	217	218	219	220
56	221	222	223	224
57	225	226	227	228
58	229	230	231	232
59	233	234	235	236
60	237	238	239	240
61	241	242	243	244
62	245	246	247	248
63	249	250	251	252
64	253	254	255	256